

### Features

#### MX Technology addressable smoke sensor, heat sensor and multi-sensor features:

- **Smoke Sensors** provide accurate photoelectric sensing
- **Heat Sensors** provide electronic heat sensing with multiple alarm options
- **Multi-Sensors** combine photoelectric sensing with heat sensing
- **Isolator Bases** monitor line condition and separates input from output to isolate short circuits
- **Sounder Bases** provide multiple tone and volume selections and are available as MX Loop powered, or powered from separate 24 VDC
- **Accessories** include remote LED indicators, address flags and labels, and base adapters
- Smoke sensors and accessories are UL listed to Standard 268, heat sensors to Standard 521

#### Compatibility:

- For use with Simplex® 4100ES, 4010ES and 4100U Series fire alarm control panels equipped with an MX Loop Module
- Analog sensor information is communicated to the host control panel and analyzed using the MX Fastlogic algorithm
- The MX Fastlogic algorithm is considered an Expert algorithm that uses real fire data as a basis for the alarm decision

#### Installation and Service Features:

- Each sensor is supplied with an integral dust cover for protection during storage and installation and is easily removed when commissioning the system
- Unique 'park' position for commissioning and service
- The address flag is attached to the base to minimize errors during service
- Detector addressing is conveniently programmed using the MX Service tool
- Bases with multiple mounting options simplify installation

### Description

**Rugged Construction.** MX compatible 4098-Series sensors provide robust and reliable construction which has undergone stringent environmental testing. Electrical contacts are molded into the plastic to eliminate movement. Construction uses durable, fire resistant FR110 plastic.

**Detection Modes.** MX Sensors communicate to the MX Loop Module using MX Technology communications. This allows each detector to operate in one or two of several detection modes, thus allowing it to be easily optimized to the risk.



4098-5202 Photoelectric Sensor and 4098-5203 Photoelectric Sensor with Heat Sensing



4098-5201 Heat Sensor



4098-5207 Standard Base and 4098-5208 Isolator Base



4098-5209, 4098-5210, and 4098-5211 Sounder Bases

\* Listings under Simplex Time Recorder Co. are the property of Tyco Fire Protection Products.

## MX Fastlogic Sensor Operation

**MX Fastlogic sensor operation** is an algorithm that takes into account the pattern of smoke build up over time and applies fuzzy logic to calculate the level of risk. This algorithm uses over 200 years of fire test data from research at the University of Duisburg (Duisburg, Germany) to determine the likelihood that there is a real fire and is designed to achieve faster detection of real fires and slower (preferably no detection) of false alarm sources.

**MX Fastlogic Sensor Basics.** The MX Fastlogic algorithm can be described as an Expert algorithm since it uses real fire data as a basis for the alarm decision. For any given application we are obliged to employ the most suitable detection in terms of response to an actual fire while minimizing false alarms. This general requirement is clearly reflected in local and national standards governing fire detection system designs.

Traditionally, attempts at reducing the occurrence of false alarms have involved degrading the level of fire protection afforded, either by raising the alarm threshold of smoke detectors, introducing delays, or generally employing less responsive detection. MX Fastlogic sensors give us the opportunity to offer an improved level of protection while simultaneously increasing immunity to false alarm.

### MX Fastlogic Algorithm - Principle Elements.

Several elements of the detector output are monitored and this raw data is used by MX Fastlogic algorithm to execute a series of processes to evaluate the probable presence of fire including:

- Background filtering
- Instantaneous smoke density
- Rate of change of smoke density
- Smoke density weighting
- Smoke density peak suppression
- Real fire 'experience' comparison

Elements synonymous with false alarms are filtered while those elements indicative of fire are weighted. These results are continually compared against data derived from real fires to produce a measure of fire risk. It is against this risk measurement that the decision to alarm is made.

### Maintain Sensitivity and Minimizing False Alarms.

MX Fastlogic sensors are designed to maintain sensitivity to fire while minimizing false alarms. Many analog detection systems allow the user to select different smoke detector sensitivity settings e.g. High, Normal, or Low sensitivity. Lowering the sensitivity setting is a typical reaction to unwanted alarms but it usually means that a greater density of smoke is required to initiate an alarm. This is not the case for detectors using MX Fastlogic operation which is comparing the real fire experience against recognized fire patterns. Changing sensitivity from 'normal' to 'low' for example, would delay responses to less likely fire patterns while maintaining a normal response to more likely fire patterns. The net result is a reduced sensitivity to possible false alarms without reducing sensitivity to clearly identifiable fires.

**MX Fastlogic availability.** MX Fastlogic operation is available for MX photoelectric sensors and photoelectric/heat sensors. These devices are used in both life protection and property protection applications providing reliable, early detection of real fires.

## Soft Addressing

MX technology sensors and addressable devices are addressed using the 801AP programming tool which presents a simple menu driven user interface that can automatically increment addresses following each write operation. This simple to use "soft addressing" technique avoids misaddressing errors that often occur when coded switches are used.

The 801AP address programmer can also change addresses stored in a sensor or other addressable device's non-volatile memory, which makes addressing errors easy to rectify.

## Sensor Details



4098-5201 Heat Sensor

**4098-5201 Heat Sensor.** The 4098-5201 Heat Sensor returns analog temperature readings to the fire alarm control panel for evaluation. Construction includes a high quality thermistor with very low thermal mass allowing the sensor to provide fast and accurate temperature readings for heat detection determination.

Heat detection settings are selectable at the fire alarm control panel for 135° F (57.2° C) or 200° F (93° C) either with or without rate-of-rise detection.

**Application Note:** When Heat Sensor 4098-5201 is used for 200° F setting applications, only use the following bases:

- Standard Base 4098-5207
- Isolator Base 4098-5208
- Sounder Base 4098-5210

## Sensor Details (Continued)



4098-5202 Photoelectric Sensor

**4098-5202 Photoelectric Sensor** incorporates a unique optical chamber design with a signal-to-noise ratio that provides high resilience to dust, dirt, and small insects for reduced service cost. The unique chamber cover actually draws slow moving smoke into the chamber to provide more responsive detection.



4098-5203 Photoelectric Sensor with Heat Sensing

**4098-5203 Multi-Sensors** provide the features of the 4098-5202 photoelectric sensor with the addition of the heat sensor from the 4098-5201. This allows the 4098-5203 to satisfy detection applications with multiple risks.

## Additional MX Loop Module Information

For additional information about the MX Loop Module, refer to data sheet S4100-0059.

## Base and LED Indicator Details




4098-5207 5" Addressable Sensor Base

**4098-5207 5" Addressable Sensor Bases** are compatible with a variety of standard ceiling and wall mount backboxes. Features include: Remote LED connections, Anti-Tamper facility, Park position and address flag holder, and integral breakout locking key.




4098-5208 Addressable Isolator Base

**4098-5208 Addressable Isolator Bases** provide the features of the 4098-5207 Standard Base and incorporate bi-directional short circuit isolation. Isolators can be used for each sensor on the MX Loop, or can be used to isolate specific areas, as well as to isolate sensors from callpoints, manual stations, and other MX addressable devices. An integral yellow LED indicates isolation mode is activated.



2098-9808 Remote LED Indicator

**2098-9808, Remote LED Alarm Indicator.** Red LED indicator provides a remote indication that the sensor is in Alarm. (Refer to Specifications on page 5 for dimensions.)



4098-5209, 4098-5210, and 4098-5211 Sounder Bases,  
Appearance Reference (shown with supplied mounting flange)

### Sounder bases are for use with the following sensors:

- 4098-5201, Heat Sensor (see application note on page 2)
- 4098-5202, Photoelectric Sensor
- 4098-5203, Photoelectric Sensor with Heat Sensor

### Multiple output tones are available:

- Tones are activated per individual address as controlled from the MX Loop Module
- Eight tone selections are available (see details below)
- Tone is DIP switch selected at the base to satisfy local requirements

### Tone volume is adjustable at each base:

- For applications requiring reduced sound level, output volume can be adjusted at the sounder base using Volume Trimmer Tool 517.050.015

### MX Loop Module provides the following tone control selections:

- Temporal 3
- Slow March Time (20 bpm)
- March Time (60 bpm)
- Steady-on (continuous)

### Local tone selection options:

- **Continuous** – *Note: Select this for use with Temporal 3, Slow March Time, or March Time control from the MX Loop Module*
- The following local tone selections are available for use with the Steady-on (continuous) command from the MX Loop Module:
  - **Temporal 4**
  - **Slow sweep**
  - **March time beep**
  - **Fast sweep**
  - **Temporal 3**
  - **Two tone**
  - **German DIN**
  - **Dutch Slow Sweep**

### 4098-5209 Addressable Loop Powered (LP) Sounder Base, Low Output:

- MX Loop powered, no separate power connection is required
- Maximum sound level output is 85 dBA @ 3 ft (1 m)
- Maximum alarm current is 6.8 mA, from the MX Loop
- Note: 4098-5209 is for supplemental use only and not in lieu of notification appliances

### 4098-5210 Addressable Loop Powered (LP) Sounder Base, Standard Output:

- MX Loop powered, no separate power connection is required
- Maximum sound output is 85 dBA @ 10 ft (3 m)
- Maximum alarm current is 24 mA, from the MX Loop

### 4098-5211 Addressable 4-Wire Sounder Base:

- Sounder is activated from the MX Loop
- Power is supplied from a separate 24 VDC fire alarm power supply using a separate wiring loop
- Maximum sound output is 90 dBA @ 10 ft (3 m)
- Maximum alarm current is 20 mA, from the separate fire alarm power supply

## Product Selection

Model	Description	Installation Instructions
4098-5201	Heat Sensor	579-933
4098-5202	Photoelectric Smoke Sensor	579-934
4098-5203	Photoelectric Smoke Sensor with Heat Sensor (Multi-Sensor)	579-932
2098-9808	Remote LED Alarm Indicator	—
4098-5207	5" Addressable Sensor Base with Remote LED Output	579-936
4098-5208	5" Addressable Isolator Base with Remote LED Output	579-937
4098-5209	Addressable Loop Powered (LP) Sounder Base, Low Output [85 dB @ 3 ft (1 m)]	579-939
4098-5210	Addressable Loop Powered (LP) Sounder Base, Standard Output [85 dB @ 10 ft (3 m)]	579-925
4098-5211	Addressable 4-Wire Sounder Base	579-926

## Sensor Accessories

Model	Description	Installation Instructions
4098-5275	6" Adapter for the 5" Base	579-938
4098-5276	Address Flags (pack of 100)	refer to base instructions
4098-5277	Address Flag Labels	
517.050.015	Volume Trimmer Tool	used with sounder bases

## Specifications

### Current Requirements (except for 4098-5211, 4-Wire Sounder Base, all currents are supplied from the MX Loop)

Product	Normal	In Alarm/Activated (Note: Does not include Remote Indicator LED current)
4098-5208 Isolator Base	80 $\mu$ A	10 mA in isolation
4098-5201 Heat Sensor	245 $\mu$ A	3.33 mA maximum in alarm
4098-5202 Photoelectric Sensor	275 $\mu$ A	
4098-5202 Multi-Sensor	275 $\mu$ A	
4098-5209 LP Sounder Base	200 $\mu$ A	6.8 mA at full volume of 85 dB @ 3 ft (1 m) 1.2 mA at low volume
4098-5210 LP Sounder Base	10 $\mu$ A	24 mA at full volume of 85 dB @ 10ft (3 m)
4098-5211 4-Wire Sounder Base	5 $\mu$ A	20 $\mu$ A from MX Loop
		20 mA from external 24 VDC power

### General Specifications

Communications	MX Loop, 1 address per sensor base
Sounder Base Voltage	18 to 32 VDC; (24 VDC nominal) from fire alarm power supply
Sensor Base Wire Connections	Terminal blocks, for wire size 20 to 14 AWG (0.5 to 2.5 mm <sup>2</sup> , or two, 1.5 mm <sup>2</sup> )

### Operating Temperature Range:

4098-5203 Multi-Sensor 2098-9808 Remote LED Annunciator 4098-5210 LP Sounder Base 4098-5211 Four Wire Sounder Base	32° to 100° F (0° to 38° C)
4098-5209 LP Sounder Base	32° to 100° F (0° to 38° C); 100° F (38° C) maximum ceiling ambient temperature
4098-5202 Photoelectric Sensor 4098-5207 Standard Base 4098-5208 Isolator Base	-13° to 158° F (-25° to 70° C) continuous; up to 194° F (90° C) short term
4098-5201 Heat Sensor	135° F (57.2° C) setting
	200° F (93° C) setting
	100° F (38° C) maximum ceiling ambient temperature
	150° F (65.6° C) maximum ceiling ambient temperature

### Additional Specifications:

Humidity Range	up to 93% RH at 90° F (32° C)	
Sensor Dimensions	4 1/4" (109 mm) diameter x 1 1/16" (43 mm) deep	
Base Dimensions (Standard and Isolator)	5" (125 mm) diameter x 15/16" (23.5 mm) deep	
Sounder Base Dimensions	4 11/32" (110 mm) diameter x 1 15/32" (37.5 mm) deep	
2098-9808 Remote LED Indicator	Dimensions	Overall: 4 1/2" H x 2 3/4" W (114 mm x 70 mm) Mounting holes: 3 9/32" (83 mm) apart (standard US single-gang box mounting)
	Current	1 mA
	Connections	Color coded wire leads, 18 AWG (0.82 mm <sup>2</sup> )

*TYCO, SIMPLEX, and the product names listed in this material are marks and/or registered marks. Unauthorized use is strictly prohibited.*



Tyco Fire Protection Products • Westminster, MA • 01441-0001 • USA  
[www.simplexgrinnell.com](http://www.simplexgrinnell.com)

S4098-0045-1 11/2011

© 2011 Tyco Fire Protection Products. All rights reserved. All specifications and other information shown were current as of document revision date and are subject to change without notice.