

# NC-100R(A)

## Relay Module for FireWarden Series Panels


**Addressable**

### General

The **NC-100R(A)** Addressable Relay Module provides NOTIFIER's **FireWarden Series** intelligent control panels with two isolated sets of Form-C dry-contact outputs for activating a variety of auxiliary devices, such as fans, dampers, door holders, control equipment, etc. Addressability allows the dry contact to be activated, either manually or through panel programming, on a select basis.

### Features

- Built-in type identification automatically identifies these devices to the control panel.
- Internal circuitry and relay powered directly by two-wire SLC loop.
- Integral LED "blinks" green each time a communication is received from the control panel and turns on in steady when activated.
- High noise immunity (EMF/RFI).
- Wide viewing angle of LED.
- SEMS screws with clamping plates for wiring ease.
- Direct Decade entry of address: 01 – 99 with the FireWarden-100-2(C) and 01 – 50 with the FireWarden-50(C).

### Applications

The NC-100R(A) may be programmed to operate dry contacts for door holders, Air Handling Unit shutdown, etc., and to reset four-wire smoke detector power.

### Construction

- The face plate is made of off-white heat-resistant plastic.
- Controls include two rotary switches for direct-dial entry of address setting.
- The NC-100R(A) provides two Form-C dry contacts that switch together.

### Operation

Each NC-100R(A) uses one of the addresses on a SLC loop. It responds to regular polls from the control panel and reports its type and status. The LED blinks with each poll received. On command, it activates its internal relay.

Rotary switches set a unique address for each module. The address may be set before or after mounting. The built-in TYPE CODE (not settable) will identify the module to the control panel.



NC-100R(A)

### Specifications

**Normal operating voltage:** 15 to 32 VDC.

**Maximum SLC current draw:** 6.5 mA (LED).

**Average operating current:** 230  $\mu$ A direct poll (CLIP mode), 255  $\mu$ A group poll with LED flashing.

**EOL resistance:** not used.

**Temperature range:** 32°F to 120°F (0°C to 49°C).

**Humidity range:** 10% to 93% non-condensing.

**Dimensions:** 4.5" (11.43 cm) high x 4" (10.16 cm) wide x 1.25" (3.175 cm) deep. Mounts to a 4" (10.16 cm) square x 2.125" (5.398 mm) deep box.

### Relay Contact Ratings

| Load Description    | Application | Maximum Voltage | Current Rating |
|---------------------|-------------|-----------------|----------------|
| Resistive           | Non-Coded   | 30 VDC          | 3.0 A          |
| Resistive           | Coded       | 30 VDC          | 2.0 A          |
| Resistive           | Non-Coded   | 110 VDC         | 0.9 A          |
| Resistive           | Non-Coded   | 125 VAC         | 0.9 A          |
| Inductive (L/R=5ms) | Coded       | 30 VDC          | 0.5 A          |
| Inductive (L/R=2ms) | Coded       | 30 VDC          | 1.0 A          |
| Inductive (PF=0.35) | Non-Coded   | 125 VAC         | 0.5 A          |

## Agency Listings and Approvals

In some cases, certain modules may not be listed by certain approval agencies, or listing may be in process. Consult factory for latest listing status.

- **UL/ULC Listed:** S635.
- **CSFM approved:** file 7300-0028:230.
- **FM approved.**
- **MEA approved:** file 72-01-E, Vol. 2.

## Product Line Information

**NC-100R:** Intelligent addressable relay module.

**NC-100RA:** Intelligent addressable relay module, ULC listed model.

**SMB500:** Optional surface-mount backbox.

**NOTE:** For installation instructions, see document 156-2593-001 and refer to the SLC Wiring Manual, document 52304.

---

**NOTIFIER®** is a registered trademark of Honeywell International Inc.  
©2010 by Honeywell International Inc. All rights reserved. Unauthorized use of this document is strictly prohibited.

---



This document is not intended to be used for installation purposes.  
We try to keep our product information up-to-date and accurate.  
We cannot cover all specific applications or anticipate all requirements.  
All specifications are subject to change without notice.

For more information, contact Notifier. Phone: (203) 484-7161, FAX: (203) 484-7118.  
[www.notifier.com](http://www.notifier.com)



Made in the U.S. A.