

Goal: How to Identify 2001 Zone Module Compatibility for 2-Wire Smoke Detector

Symptoms:

- Need to replace smoke detector
- Need information
- Need module information
- What modules are used with which control modules
- Need zone module to control module cross reference information

Cause:

- Not all 2001 zone modules are capable of supporting 2-wire smoke detector operation.

Fix:

- We are pleased to announce that Tyco Safety Products has obtained compatibility Listing from Underwriters Laboratories (UL) for TrueAlarm Detectors with legacy 2001 Control Panels!
- To read all the details, please click on the link below to view this very important bulletin!
- Refer to the [Sales Engineering Bulletin SSD Detectors Compatible with 2001 Simplex Controls SEB-FAS 06-004](#)
- Refer to the [SSD's Compatible With 2001 Control Panels](#)
- Non 2-wire smoke zone modules were primarily on older full size 2001 "Family 1" systems...
- The following 2001 Zone modules as listed:
- Typically used with Fire/Trouble Control Module 2001-2001,2,3,4 (556-237, -238, -239, -240)

2001 Module		Device type	Notes
2001-2010	556-218	N/O devices only	Dual zone monitor use 4-wire smoke detectors
2001-2012	556-218	N/C devices only	
2001-2013	556-246	N/O devices only	Class A zone monitor
2001-2014	556-300	N/O devices only	

- Typically used with Separate Fire and Trouble Control Modules 2001-1002 / 2001-1005 (556-233 / 556-236)

2001 Module		Device type	Notes
2001-1010	556-217	N/O devices	Single zone w/ test switch
2001-1011	556-220	N/O devices	Single zone no switch
2001-1012	556-221	N/C devices	Single zone
2001-1013	556-301	N/O devices	Single zone no switch
2001-1016	556-551	N/O devices	Single zone w/ switch

- Typically used in systems with 2001-1007 (556-880)

2001 Module		Device type	Notes
2001-1017	556-082	2-wire smokes	Dual zone monitor
2001-1018	556-916	2-wire smokes	Single zone class A monitor
2001-1019	556-896	2-wire smokes	Dual zone w/ test switch
2001-1020	556-540	2-wire smokes	Single class A w/ test switch

Facts:

- 2001
- Fact: 4-wire Smoke Detector
- Fact: 2-wire Smoke Detector
- Fact: cross reference information