

LIFE SAFETY  $\mathscr{G}$  INCIDENT MANAGEMENT

# Hazardous Location Strobes



#### Overview

116DEGEX-FJ hazardous location strobes are life safety signaling appliances designed for installation in hazardous environments. Rigid specifications and state-of-the-art technology provide for high visual output and low maintenance. The 116DEGEX-FJ has negligible in-rush current.

When pendant, wall or ceiling mounted, the 116DEGEX-FJ meets or exceeds the requirements of *UL 1971 Signaling Appliance for the Hearing Impaired*.

The 116DEGEX-FJ is intended for indoor use in UL 1971 (signal appliance for the hearing impaired) listed compatible fire alarm systems. The strobe flashes a 360-degree beam of light approximately at 1 Hertz (65 times per minute) with a UL 1971 125 cd ceiling and 60 cd wall light output. With the guard installed, the strobe flashes a beam with an output of 86 cd ceiling and 51 cd wall. The strobe is also UL 1638 (visual signal appliance, private mode) listed with dome guard installed for both indoor and outdoor use, and other applications requiring electrical supervision of the signaling circuit field wiring. The 116 Class strobes are cUL listed to Canandian Standard ULC-S526-07 (Visual Signal Device for Fire Alarm Systems), suitable for indoor and outdoor applications. The strobe features an enhanced synchronization circuit to comply with the latest requirements of UL 1971 and CAN/ULC-S526-07. Synchronized operation requires a separately installed synchronization control module. See Ordering Information for details.

When assembled with one of the three available mounting options, the 116DEGEX-FJ is UL Listed for use in Class I, Division 1, Groups C and D, Class I, Division 2, Groups A, B, C and D, Class II, Division 1, Group E, F and G, Class II, Division 2, Group F and G, and Class III Division 1 and 2 hazardous locations. The strobe is also cUL Listed as a Type 3R and 4X enclosure.

#### Standard Features

- UL 1971 listed and ADA compliant for the hearing impaired
- Negligible in-rush current
- Approved for fire alarm applications
- Wall, ceiling or pendant mount
- Diode-polarized for use in electronically supervised circuits
- High-impact glass dome
- 1 Hertz flash rate (65 flashes per minute)
- Synchronized with external module
- 60 cd wall or 125 cd ceiling, per UL 1971
- Factory sealed no external seals required
- Quick connect threads onto mounting module for easy installation
- Epoxy powder coat for corrosion resistance
- cUL listed to CAN/ULC-S526-07 and UL 1638 for indoor and outdoor applications

## Application

116DEGEX-FJ hazardous location strobes are designed for use in compatible EDWARDS fire alarm systems and other applications requiring electrical supervision of signaling circuit field wiring.

These strobes are suitable for many locations including mines, graineries, flour mills, tankers, refineries, laboratories and other applications where environmental hazards may be present. 116DE-

## Wiring



GEX-FJ strobes are particularly well-suited in areas of high noise levels where standard bells or horns are not satisfactory.

When pendant, wall or ceiling mounted, 116DEGEX-FJ strobes are cUL listed to CAN/ULC-S526-07 for indoor and outdoor applications, and UL 1971 Listed (ADA compliant) for indoor visual signaling applications in non-sleeping areas.

#### Notes:

- DC Polarity of circuit shown in supervisory state (signal inactive). Reverse circuit • polarity to activate signal.
- Electrical supervision requires wire run to be broken at each device.
- Device for constant input voltage. Do not connect to "coded" or pulsating voltage.

### Mounting

16 1/16"

(408 mm 16 13/16"

(427 mm)

Thanks to its modular design, the 116DEGEX-FJ configures for pendant, ceiling, or wall mounting. See the ordering information table for available mounting modules.

> 12 9/16" 319 mm)

\_ 9 7/16"

(240 mm)

6 4" (102 m

Set screws

-6 3/4"

(25 mm)

5/16" (79 mm)

Wall

Mount

(184 mm)



## Light Output

Effective Candela Light Output for Wall Bracket Mount Vertical Plane (Zero degree angle at side of globe)





Optional dome guard shown. Candela output readings taken without optional dome guard installed.

• UL Required CD for 60 Rating

Effective Candela Light Output for Ceiling Mount X & Y Planes (Zero degree angle at bottom of globe)



Optional dome guard shown. Candela output readings taken without optional dome guard installed.



• UL Required CD for 125 Rating



#### LIFE SAFETY & INCIDENT MANAGEMENT

Contact us...

Email: edwards.fire@fs.utc.com Web: <u>Edwards-fire.com</u>

EDWARDS is a UTC brand. 1016 Corporate Park Drive Mebane, NC 27302

 $\ensuremath{\textcircled{O}}$  2016 United Technologies Corporation. All rights reserved.

## Specifications

Pendant, ceiling, or wall
UL 1971 (indoor) and ULC-S526-07 (indoor & outdoor):
125 cd ceiling, 60 cd wall
1 Hertz (65 fpm)
cUL
Class I, Division 1, Groups C & D, Division 2, Groups A, B, C & D; Class II, Division 1, Groups, E, F & G, Division 2, Groups F & G; Class III, Divisions 1 & 2
UL 1971 listed signaling appliance for the hearing impaired, indoor, non-sleeping areas only
SIGA-CC1S, SIGA-MCC1S, SIGA-CC2A, SIGA-MCC2A, G1M-RM, BPS6A, BPS10A, APS6A, APS10A, iO64, iO500, Fireshield Plus 3, 5 and 10 zone, EST3X
Type 3R, Type 4X, cUL listed
16 - 33 Vdc, 16-33VFWR
0.505A @ 24 Vdc (regulated), 0.683A @ 24 VFWR
cUL -40 to 150 °F (-40 to 66 °C)
Clear
Xenon - clear/nominal white flash
Gray powder coat epoxy
18 lbs (8.2 kg)

#### **Operating Temperatures**

Ambient Temperature	Supply Wire Temperature Marking	Class I, Div. 2 Groups A, B	Class I, Div. 1 & 2 Groups C, D	Class II, Div. 1 Groups E, F, G, & Class III	Class II, Div. 2 Groups F, G, & Class III
40 °C (104 °F)	75 °C (167 °F)	T2B (260 °C)	T6 (85 °C)	T4A (120 °C)	T4A (120 °C)
55 °C (131 °F)	90 °C (194 °F)	T2B (260 °C)	T6 (85 °C)	T4 (135 ℃)	T4 (135 ℃)
65 °C (149 °F)	105 °C (221 °F)	T2B (260 °C)	T6 (85 °C)	T3C (160 °C)	T3C (135 °C)

#### Ordering Information

Model	Description	Ship Wt.
116DEGEX-FJ	Explosionproof Strobe, Diode Polarized	18 lbs 8.2 kg
116EX-B	Wall bracket mounting elbow	
116EX-C	Ceiling/wall mounting module	
116EX-P	Pendant mounting module - 3/4" (19 mm) NPT	
116-GRD	Lens Guard	
116-GLOBE	Replacement Globe	

10-11-16